

SAEx 25.1 – SAEx 40.1

Electrical data multi-turn actuators for open-close duty with 3-phase AC motors

Short-time duty S2 - 15 min, 380 V/50 Hz

Multi-turn actuator			Motor									
Type	Output speed [rpm]	Max. torque [Nm]	Motor type	Nominal power ¹⁾ P _N [kW]	Speed [rpm]	Nominal current ²⁾ I _N [A]	Max. current ³⁾ I _{max} [A]	Starting current I _A [A]	cos φ	Overcurr. prot. device setting [A]	AUMA power class for switchgear	
SAEx 25.1	4	2,000	ADX0 90-8/130	1.1	700	7.0	9.0	17	0.48	7.0	A2	B2
	5.6					7.0	10	17	0.48	7.0	A2	B2
	8		ADX0 90-4/130	3.0	1,400	7.0	11	38	0.80	7.0	A2	B2
	11					7.0	12	38	0.80	7.0	A2	B2
	16		ADX0 90-2/130	4.0	2,800	10	16	58	0.78	10	A2	B3
	22					10	20	58	0.78	10	A2	B3
	32		ADX0 132-4/140	7.5	1,400	22	40	120	0.65	22	A3	—
	45					22	48	120	0.65	22	A3	—
	63		ADX0 132-2/180	15	2,800	30	60	190	0.90	30	A3	—
	90					30	70	190	0.90	30	A3	—
SAEx 30.1	4	4,000	ADX0 112-8/140	2.2	700	11	15	36	0.58	11	A2	B3
	5.6					11	16	36	0.58	11	A2	B3
	8		ADX0 112-4/110	5.5	1,400	13	20	60	0.77	13	A2	B3
	11					13	23	60	0.77	13	A2	B3
	16		ADX0 112-2/140	7.5	2,800	18	28	120	0.78	18	A2	—
	22					18	30	120	0.78	18	A2	—
	32		ADX0 160-4/160	15	1,400	44	58	200	0.63	44	A4	—
	45					44	67	200	0.63	44	A4	—
	63		ADX0 160-2/215	30	2,800	65	130	370	0.88	65	A4	—
	90					65	150	370	0.88	65	A4	—
SAEx 35.1	4	8,000	ADX0 132-8/150	4.0	700	20	30	70	0.44	20	A2	—
	5.6					20	35	70	0.44	20	A2	—
	8		ADX0 132-4/140	7.5	1,400	22	48	120	0.65	22	A3	—
	11					22	55	120	0.65	22	A3	—
	16		ADX0 132-2/180	15	2,800	30	60	190	0.90	30	A3	—
	22					30	70	190	0.90	30	A3	—
	32		ADX0 160-2/214	20	2,800	40	80	260	0.90	40	A4	—
	45					40	95	260	0.90	40	A4	—
SAEx 40.1	4	16,000	ADX0 160-8/165	7.5	700	30	55	93	0.50	30	A3	—
	5.6					30	58	93	0.50	30	A3	—
	8		ADX0 160-4/160	15	1,400	44	70	200	0.63	44	A4	—
	11					44	87	200	0.63	44	A4	—
	16		ADX0 160-2/215	30	2,800	65	150	370	0.88	65	A4	—
	22					65	170	370	0.88	65	A4	—
	32		ADX0 160-2/215	30	2,800	65	200	370	0.88	65	A4	—

Notes on table

1) Nominal power P _N	Mechanical power output at motor shaft at running torque of multi-turn actuator (corresponds to approx. 50 % of maximum torque). The consumed electrical power can be calculated using the following formula: $P = U \times I \times \cos \varphi \times \sqrt{3}$
2) Nominal current I _N	Current at running torque
3) Max. current I _{max}	Current at maximum torque

Notes on installation and sizing

Motor data	Motor data is approximate. Due to usual manufacturing tolerances, there may be deviations from the values given.
------------	--

Thermoswitches/PTC thermistors	To protect against overheating, thermoswitches or PTC thermistors are embedded in the motor windings. Actuators without integral controls (AUMA NORM): Thermoswitches or PTC thermistors have to be considered within the external controls (refer to terminal plan). Note: Failure to connect thermoswitches or PTC thermistors shall void the warranty for the motor. According to EN 60079-14, a thermal overcurrent protection device (e.g. motor protection switch) must be installed for explosion-proof actuators in addition to the thermoswitches. PTC thermistors additionally require a suitable tripping device in the controls. Rating of the thermoswitches <table><tr><th colspan="2">AC current</th><th colspan="2">DC current</th></tr><tr><td colspan="2">250 V, 50 – 60 Hz</td><td>60 V</td><td>1.0 A</td></tr><tr><td>cos φ = 1</td><td>2.5 A</td><td>42 V</td><td>1.2 A</td></tr><tr><td>cos φ = 0.6</td><td>1.6 A</td><td>24 V</td><td>1.5 A</td></tr></table> Actuators with AMExC or ACExC integral controls: Thermal motor protection is already integrated.	AC current		DC current		250 V, 50 – 60 Hz		60 V	1.0 A	cos φ = 1	2.5 A	42 V	1.2 A	cos φ = 0.6	1.6 A	24 V	1.5 A																											
AC current		DC current																																										
250 V, 50 – 60 Hz		60 V	1.0 A																																									
cos φ = 1	2.5 A	42 V	1.2 A																																									
cos φ = 0.6	1.6 A	24 V	1.5 A																																									
Mains voltage, mains frequency	Permissible variation of mains voltage: ±10 % Permissible variation of mains frequency: ± 5%																																											
Switchgear sizing	For motor operation, reversing contactors (mechanically, electrically and electronically locked) or thyristors (electronically locked) can be used. Actuators without integral controls (AUMA NORM): Switchgear are supplied by the customer. We recommend specification of switchgear suitable for their rated operating power/motor power in compliance with the assigned AUMA power class. Switchgear assignment to AUMA power classes: <table><tr><th rowspan="2">AUMA power class</th><th rowspan="2">Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3</th><th colspan="2">Reversing contactor Motor power according to UL/CSA at</th></tr><tr><th>480 V AC</th><th>600 V AC</th></tr><tr><td></td><td>400 V AC</td><td></td><td></td></tr><tr><td>A1</td><td>4.0 kW</td><td>5.0 hp</td><td>5.0 hp</td></tr><tr><td>A2</td><td>7.5 kW</td><td>10 hp</td><td>10 hp</td></tr><tr><td>A3</td><td>15 kW</td><td>20 hp</td><td>25 hp</td></tr><tr><td>A4</td><td>30 kW</td><td>60 hp</td><td>60 hp</td></tr><tr><td>A5</td><td>55 kW</td><td>75 hp</td><td>100 hp</td></tr><tr><td>A6</td><td>75 kW</td><td>100 hp</td><td>125 hp</td></tr></table> <table><tr><th rowspan="2">AUMA power class</th><th rowspan="2">Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a</th></tr><tr><td>400 V AC</td></tr><tr><td>B1</td><td>6 A</td></tr><tr><td>B2</td><td>8.5 A</td></tr><tr><td>B3</td><td>16 A</td></tr></table> Actuators with AMExC or ACExC integral controls: Required switchgear in power classes A1 – A3 or B1 – B3 are already integrated in AMExC or ACExC controls. For switchgear of power classes A4 – A6, a control box is additionally required. For actuators with AMExC integral actuator controls and installed switchgear in AUMA power class A3, an optional thermal overcurrent protection device cannot be directly integrated within the AMExC. An additional control box is required. However, ACExC actuator controls can be used instead of AMExC controls. When opting for ACExC controls, the additional control box can be omitted.	AUMA power class	Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3	Reversing contactor Motor power according to UL/CSA at		480 V AC	600 V AC		400 V AC			A1	4.0 kW	5.0 hp	5.0 hp	A2	7.5 kW	10 hp	10 hp	A3	15 kW	20 hp	25 hp	A4	30 kW	60 hp	60 hp	A5	55 kW	75 hp	100 hp	A6	75 kW	100 hp	125 hp	AUMA power class	Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a	400 V AC	B1	6 A	B2	8.5 A	B3	16 A
AUMA power class	Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3			Reversing contactor Motor power according to UL/CSA at																																								
		480 V AC	600 V AC																																									
	400 V AC																																											
A1	4.0 kW	5.0 hp	5.0 hp																																									
A2	7.5 kW	10 hp	10 hp																																									
A3	15 kW	20 hp	25 hp																																									
A4	30 kW	60 hp	60 hp																																									
A5	55 kW	75 hp	100 hp																																									
A6	75 kW	100 hp	125 hp																																									
AUMA power class	Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a																																											
		400 V AC																																										
B1	6 A																																											
B2	8.5 A																																											
B3	16 A																																											